Level 1 Trigger at Belle II


H. Nakazawa (NTU)

20251022@TRG/DAQ workshop

Physics processes at Belle II

e+e>	Xsec [nb] in acceptance	Hz @6e35/cm2s	Target	
Y(4S)->BBbar	1.1	660	Physics (Hadron)	
qqbar(udsc)	3.7	2200	Physics (Hadron)	
τ+τ-	0.9	540	Physics (LowMult)	
$\mu^+\mu^-$	1.1	660	Physics/Calibration	
e+e-X	13	10000	Physics/Calibration	
e+e-(7)	300	<1800(1/100)	Calibration	
$\gamma \gamma (\gamma)$	5	30 (1/100)	Calibration	
NP	??	??	Physics (??)	
	>320	20 kHz (w/ PS)		
Total		~200 kHz (w/o PS)		
		15 Hz (requirement)		
Beam Crossing		250 MHz		


- Physics process / Beam bunch crossing < 0.1%</p>
- Most of the 0.1% is QED "background"
- Hadron+tautau < 0.002% of Beam crossing</p>



2

Outputs of Belle II Detector

- >300k channels from Belle II Detector
- Each channel just keep outputting its response (wire hit, energy, etc)
 - Digitized on FEE near Detector, "0"/"1".
 - © Continuous (system clock of 127MHz) data flow
 - Typical data width for physics events, [100 nsec, 2 usec]
 - We want to record only 30kHz times 2 usec = 60 ms = 6%.




	#ch
PXD	8
SVD	223744
CDC	14336
BPID	8192
EPID	65664
ECL	8736
BKLM	19008
EKLM	16800
TRG	

How do we record the data?

- © Record all continuous data flow, and check carefully on PCs with softwares in down stream
 - Triggerless DAQ
 - LHCb, ALICE, EIC adopt this but Belle II does not.
 - Requires huge Processing (CPU/GPU) and Storage resources
- © Record only "data of interest" to discard unwanted data and reduce data size to be sent to DAQ


How L1 detects "Data of Interest"?




- By analyzing data itself
 - © Collects available fast data from subdetector FEEs and do coarse analysis
 - #tracks, #clusters, energy sum, event topology, ... of the event with reduced granularity (TS, TC)
 - Relevant subdetector FEEs have output lines for L1
- - PALL FEEs must hold data in FIFO (ring buffer) until L1 makes decision that the data is necessary or not
- Allowed time length for L1 to consider is limited by Buffer size of the FEEs
- The decision making is done at every 127MHz. ~500 nsec dead time if L1 is fired.


Requirement of L1 Trigger

- Weigh efficiency, ~100% for hadron (ntrk >= 3) events
- Redundant and independent TRG logics
 - Track and Energy trigger
- Good background reduction necessary
- ©Event Timing Resolution ~10 nsec. Limited with SVD FEE.



4.4 usec





Universal Trigger Boards, UT3/UT4

- Widely used in L1 system
 - Optical Links
 - LVDS for parallel connection
 - NIM I/O x 11 x 2
 - RJ45 x 4 for Belle2Link
 - JTag for Firmware download
- Transition to UT4 ongoing
 - **©KLMTRG** and NNs are UT3




	1.1		
	UT3	$\mathrm{UT4}$	
FPGA	Xilinx Virtex6	Xilinx Virtex Ultrascale	
rrga	XC6VHX380/560T	XCVU080/160/190	
number of logic cells	382k/580k	975k/2026k/2350k	
TO	GTH 5Gbps x24lane	GTY 25Gps X 32lane	
IO	${\rm GTX}~3{\rm Gps}~{\rm x40lane}$	GTH 12.5Gps X 32lane	





Sub Triggers

CDC Trigger: TSF

- - SLO, 2, 4, 6, 8; Axial. Parallel with z axis
- TS: Priority hit and Pre Defined Wire hit pattern from signal track
 - © Effective for > 3.0 GeV/c
 - Track hit at trigger level
 - Pyramid shape in SLO, hourglass shape in SL1-8









2D Track finder

- Only Axial TS, no z information
- Track finding based on Hough Transformation for TS hits
- 1/r-phi plane, assuming a track pass through IP, remaining
 #parameter is 2 => 2D parameter space.
- © 2D track has 2D parameter at intersection of 2D param space


Hough Transformation







Single Track Trigger

- Using 2D track from 2D track finder and stereo TS hits (priority wire hit timing)
- One hidden layer, 81 nodes
- Training in offline track analysis






Single Track Trigger





- Apply |z| < 15 cm</p>
- Provides 2 trigger bits
 - At least one NN track, "y". Associated with 2 or 3 trk bits.



Much better performance that 2D tracker


The first fully operating global L1 track trigger based on neural networks has been realized.



Belle II L1

13

Full hit algorithm: Upgraded 2D Finder




BG=2020


Table 5.2: Comparison between the trigger rates caused by fake tracks of the Full-Hit 2D and of the conventional 2D. The errors are statistical errors calculated by the Clopper-Pearson method.

BG level	trigger	rate /kHz (full-hit :	2D) trigger rate (conventional 2D) /kHz
BGx10 4	e35	$0.0^{+0.18}_{-0.0}$	$7.0^{+3.7}_{-2.6}$
BGx15 6	e35	$0.0^{+0.18}_{-0.0}$	141^{+12}_{-11}
BGx20 8	e35	$7.0^{+0.8}_{-0.9}$	695^{+15}_{-15}

- Wire hits of fake track are not aligned with the fake track but satisfiesTS pattern matching
 - © Conventional 2D Track finder does not use hit pattern in TS but use only priority wire info
- Full-hit algorithm where all wire hit is used for track reconstruction allows us significant fake track reduction in future high BG

ECLTRG






Analog sum of 16 crystals taken on FAM to reduce granularity for coarse online analysis with limited time and resources


=> TC (Trigger cell)

- TMM merges TC info
- ETM reconstruct cluster
 - #cluster, Esum, Bhabha, Timing to GDL
 - TC info (timing/geometry/energy) to GRL




- 1 Algorithm of clustering for position
- 2 Timing determined with the central TC
- 3 Energy of the Cluster is sum of 9 TCs

ECLTRG



Timing Signal Generation on FAM



- Fit energy (ADC) distribution to determine the deposited energy and hit timing of the TC signals
- Timestamp of the peak (latency since collision) is obtained by template fit
- Timestamp of the most energetic
 TC is sent to GDL
- 4 GDL generate L1 signal after constant offset studied beforehand if physics event is detected


timestamp:

counter in 0,..,1279 with 127 MHz sysclk 10 usec cycle, one beam revolution

TOPTRG/KLMTRG

- **OPTRG**
 - © 2 nsec precision MCPPMT hits in 16 modules sent from FEE to TOPTRG


 - Timing resolution of 10 nsec achieved
 - Filtered with CDCTRG through matching
- KLMTRG
 - Layer-Counting Trigger (LCT) algorithm
 - Sector-based counting. Fired if #count>8.



GRL (Global Reconstruction Logic)


- © Receives particle level information from subtriggers and take coincidence of the particle in different subtriggers.
 - ©Trk-Clster, Trk-KLMTRG hit, Trk-TOP
- @Latency is tight. LVDS (serial) connection used for GRL ->
 GDL.


Generates short track



GDL (Global Decision Logic)


- Summary module of L1 system
- Implemented on a UT4
- Issues L1 signal to FTSW (Timing Distribution)






Injection veto

- To Keep beam current, Beam injection is made even during data taking
 - Background level surges for short period after injection. We must not take data.
 - Injection rate 25 Hz at most. Injection background disappears by the next injection.
 - L1 applies veto in the period applying "& !veto" in logic
 - Full veto
 - Gate veto1: wider time window around injected bunch
 - Gate veto1: narrower time window around injected bunch
- SKB provides GDL injection kicker signal through NIM cable
- Time window size and length are adjusted automatically based on data in the past 15 mins and updated at the next run








20

Injection veto: active injection veto

- Injection veto causes large dead time
 - => Even in veto-period of ①-③, take data (issue L1 signal) if #TC hit and #wire hit is lower than threshold to reduce dead time
 - Injection veto is severe in Endcap region, we set partwise threshold for #TC. Leakage of injection background events disappear.







Input Triggers

	nbits	name	
	4	n_ty	#of NN tracks
	4	n_t2	#of 2D tracks
CDC	1	cdc_bb	back-to-back topology
CDC	1	cdc_open90	opening angle
	1	cdc_timing	timing signal
	1	typ	Single Track
	1	e_high	1 GeV or more
	1	e_low	0.5 GeV or more
	1	ecl_3dbha	Bhabha event
ECL	4	n_clus	# of cluster
	1	ecl_timing	timing signal
	1	ecl_lml_1	Single Cluster >2GeV in Brl
	14	ecl_lml_X	Low Multiplicity Analysis

Input Triggers

	nbits	name		
TOP	1	top_timing	Top Timing	
	3	n_klm	# of klm hits	
KLM	1	klmb2b	Back-to-Back in Brl	
	1	eklmb2b	Back-to-Back in Ecp	
	1	revo	Beam Revolution	
Random	2	rand	Poisson	
	3	bhabha_delay	Background overlay data	
	4	cdcecl_X	CDC-ECL matching	
GRL	2	cdcklm_X	CDC-KLM matching	
	1	ecleklm	ECL-EKLM matching	

Trigger Outputs: Logic


Output bit		PS	Logic = algorithm
stt	Single track	1	typ & !bha_veto
lml1	1 Cluster	1	ecl_lml_1
ffy	hadron	1	t2 > 2 & ty > 0
fyo	2 track	1	t2 > 1 & cdc_open90 & ty > 0 & !bha_veto
hie	1 GeV	1	e_high & !bha_veto
с4	4 clusters	1	n_clus > 3
Bha3d	Bhabha	100	ecl_3dbha
ggsel	ee $\rightarrow \gamma \gamma$	1	ecl_3dbha & (!trkbha1 & !trkbha2) & bha_intrk
mu_b2b	mu pair	1	klmb2b
revolution		1	revo
random	random	1	rand
bg		1	bhabha_delay


Injection veto applied, "&!veto", to all bits

Trigger Efficiency from experiment data


- Experiment data is survival biased.
 - Mask with orthogonal trigger, Track <=> Energy.


Energy Trigger Efficiency With Track mask






Trigger Efficiency for hadron events: CDCTRG






- ©Efficiency slightly decreased in 2024bc
- Reason unknown but can be due to masked merger or CDC Gas
- Various triggers complement each other.
 Total inefficiency,
 (1-ε₂)(1-ε₂)(1-ε₃)(1-ε₄)...
 is negligibly small for hadron events.

Trigger efficiency for hadron events: ECLTRG




- Basically stable. > 95%.
- Problematic shaperDSP caused low efficiency in Energy sum and cluster counting bits

Trigger Efficiency: KLMTRG



Efficiency OK

L1 rate



29

Summary

©L1 Trigger at Belle has worked well.

- Almost 100% efficiency for hadron data taking
 - Independent Triggers complement each other

- Trigger rate well before the DAQ limit
 - Many efforts to reduce background has been made
 - Neuro Trigger, full-hit algorithm, Injection veto, etc.


S

Machine Parameters


2017/September/1	LER	HER	unit	
E	4.000	7.007	GeV	
	3.6	2.6	Α	
Number of bunches	2,5	00		
Bunch Current	1.44	1.04	mA	
Circumference	3,016	5.315	m	
$\epsilon_{x}/\epsilon_{y}$	3.2(1.9)/8.64(2.8)	4.6(4.4)/12.9(1.5)	nm/pm	():zero current
Coupling	0.27	0.28		includes beam-beam
β_x^*/β_y^*	32/0.27	25/0.30	mm	
Crossing angle	8	3	mrad	
α_{p}	3.20x10 ⁻⁴	4.55x10 ⁻⁴		
σδ	7.92(7.53)x10 ⁻⁴	6.37(6.30)x10 ⁻⁴		():zero current
V _c	9.4	15.0	MV	
σ_{z}	6(4.7)	5(4.9)	mm	():zero current
Vs	-0.0245	-0.0280		
v_x/v_y	44.53/46.57	45.53/43.57		
U₀	1.76	2.43	MeV	
$\tau_{x,y}/\tau_s$	45.7/22.8	58.0/29.0	msec	
ξ _× /ξ _γ	0.0028/0.0881	0.0012/0.0807		
Luminosity	8x10 ³⁵		cm ⁻² s ⁻¹	

	SuperKEKB:	Dec. 27, 2024	SuperKEKB:	Unit	
Ring	LER	HER	LER	HER	
Emittance	4.0	4.6	4.0	4.6	nm
Beam Current	1632	1259	744	600	mA
Number of bunches	23	46	15	65	
Bunch current	0.696	0.537	0.475	0.383	mA
Horizontal size σ _x *	15.5	16.6	17.9	16.6	μm
Vertical cap sigma Σ _y *	0.375		0.250		μm* ¹
Vertical size σ _y *	0.265		0.177		μm* ²
Betatron tunes v _x / v _y	44.525 / 46.589	45.531 / 43.599	44.525 / 46.589 45.532 / 43.574		
β _x * / β _y *	60 / 1.0	60 / 1.0	80 / 0.8	60 / 0.8	mm
Piwinski angle	12.3	12.7	10.7	12.7	
Crab waist ratio	80	60	80	40	%
Beam-Beam parameter ξ _y	0.036	0.027	0.031	0.022	
Specific luminosity	5.8 x 10 ³¹		8.7 x 10 ³¹		cm ⁻² s ⁻¹ /mA ²
Luminosity	5.1 x	10 ³⁴	2.5 x 10 ³⁴		cm ⁻² s ⁻¹

^{*1)} estimated by luminosity with assuming design bunch length *2) divide *1 by $\sqrt{2}$



Component of L1 rate




91.5 - 4 higher beam background than 2024ab

- No beam background effect on ECL and KLM trigger rate
- 91 1.5 higher CDCTRG rate than 2024ab thanks to ADC cut introduced 2024c


CDCTRG efficiency drop

-CDCTRG efficiency is not stable


- -~2% by dead CDCFE and MGR
- -~6% by CDC detector gain drop (large effect if CDC dE/dx < 0.9)



CDCTRG 2track efficiency



Skim Ratio



- Both hadron/bhabha and mumu/bhabha decreased
- No impact from Injection background
- HER optics change or update of globaltag might affect this (gitlab)
- Monitor (DQM) from software group needed

Acceptable beam background by TRG

- -Roughly say, Trigger rate is linearly proportional to beamBG
- -Trigger rate will be 15kHz with "CDC current ~450μA" or "TOP PMT ~9MHz" equivalent beamBG condition
- -With tighter trigger menu, further ~50% reduction of trigger rate is expected

